## HALO Series L.E.D. Hide-A-Way Lights



WIRING INSTRUCTIONS				
RED	Apply to Positive for Activation of COLOUR 1			
PURPLE	Apply to Positive for Activation of COLOUR 2			
***Combine both <b>RED</b> + <b>PURPLE</b> wires to Activate both COLOUR 1 + 2***				
BLACK	Apply to Negative for Ground			
WHITE	Apply to Negative for Dimming			
BLUE	Momentarily Apply to Negative for Pattern Change			
***Connect <b>BLUE</b> wires to SYNCHRONISE Multiple Units***				
YELLOW	YELLOW Apply to Negative for Steady-On			
Momentarily Apply <b>BLUE</b> wire to Negative to change the COLOUR of Steady-On function, when activated.				

## WARNING NOTICE HIGH INTENSITY BRIGHTNESS | DO NOT STARE DIRECTLY INTO LIGHT

PATTERN LIST					
SINGLE COLOUR		DUAL COLOUR			
P1	FULL – Fast Single Flash *A*	P1	FULL – Fast Single Flash *A*		
P2	FULL – Fast Single Flash *B*	P2	2 FULL – Fast Single Flash *B*		
P3	FULL – Fast Double Flash *A*	<b>P</b> 3	FULL – Fast Double Flash *A*		
P4	FULL – Fast Double Flash * <b>B</b> *	P4	FULL – Fast Double Flash *B*		
P5	FULL – Fast Quad Flash *A*	P5	FULL – Fast Quad Flash *A*		
P6	FULL – Fast Quad Flash * <b>B</b> *	P6	FULL – Fast Quad Flash * <b>B</b> *		
P7	FULL – Slow Single Flash *A*	P7	FULL – Slow Single Flash *A*		
<b>P8</b>	FULL – Slow Single Flash * <b>B</b> *	<b>P8</b>	FULL – Slow Single Flash * <b>B</b> *		
P9	FULL – Slow Double Flash *A*	<b>P9</b>	FULL – Slow Double Flash *A*		
P10	FULL – Slow Double Flash * <b>B</b> *	P10	FULL – Slow Double Flash *B*		
P11	FULL – Slow Quad Flash * <b>A</b> *	P11	FULL – Slow Quad Flash *A*		
P12	FULL – Slow Quad Flash * <b>B</b> *	P12	FULL – Slow Quad Flash * <b>B</b> *		
P13	FULL – Steady-Burn @ 50%	P13	FULL – Steady-Burn @ 50% *COLOUR 1*		
P14	OFF	P14	FULL – Steady-Burn @ 50% *COLOUR 2*		
Different Flash Patterns can be selected for RED, PURPLE and RED+PURPLE activation modes.		P15	OFF		

GROUPING		PROGRAMMING		
SIMULTANEOUS GROUPING	To Simultaneously flash all your lights together in one group with the same pattern at the same time, select the exact same PATTERN for each light featuring the same group, for example, all "A" or all "B".	NEXT PATTERN	Apply BLUE wire to Negative for < <b>1 Second</b>	
		PREVIOUS PATTERN	Apply BLUE wire to Negative for ≥ <b>2 Seconds</b>	
ALTERNATING GROUPING	To Alternate flash your lights in two separate groups, select " <b>A</b> " <b>pattern</b> for your first group of lights, and select " <b>B</b> " <b>pattern</b> for your second group but both groups must feature the same PATTERN to allow the two groups to alternate flash.	FACTORY RESET	Apply BLUE wire to Negative for ≥ <b>4 Seconds</b>	
		DEACTIVATE	Apply BLUE wire to Negative for > <b>5 Seconds</b>	